

1/8 DIN Dual Input Process Panel Meter

With Optional USB Communications



DP6060 Series



DP6060 shown smaller than actual size.

- ✓ **Modular USB, RS232, RS485 Serial Communication Options and Relays**
- ✓ **Math Functions: Addition, Difference, Average, Multiplication, Division, Min, Max, Weighted Average, Ratio, Concentration, and More**
- ✓ **0 to 20 mA, 4 to 20 mA, 0 to 5V, 1 to 5V, and ±10V Inputs**
- ✓ **Large Dual-Line 6-Digit Display, 15 and 12 mm (0.60 and 0.46")**
- ✓ **Sunlight Readable Display Models**
- ✓ **NEMA 4X (IP65) Front**
- ✓ **Universal 85 to 265 Vac, or 12/24 Vdc Input Power Models**
- ✓ **Isolated 24 Vdc @ 200 mA Transmitter Power Supply**
- ✓ **Free Software for Operation, Monitoring, and Programming**

The DP6060 Series process meter combines two independently programmed analog inputs with powerful math functions to make an advanced meter capable of handling complex math requirements common in the process industry. Various math functions may be applied to the inputs including addition, difference, average, multiplication, division, ratio, and more. A customizable dual-line display allows a wide variety of input variables, math calculations, or units and tags to be displayed

based on your application needs. Sunlight readable display models have an extraordinarily bright LED display. The DP6060 has two red LED displays, an upper display 15 mm (0.60") high, and a lower display 12 mm (0.46") high. Each display is a full 6 digits (-99999 to 999999). The displays can be set up to read input channels (A or B), math function channel C, toggle between A & B, B & C, A & C, A & B & C, toggle between channels A, B, or C & units, the max/min of any of the channels, including the math channel (C), set points, gross (without tare) or net (with tare) and gross values of channel A or B, or the MODBUS input. No jumpers to set for input selection. All setup and programming are done via the front panel. Three levels of password protection help maintain the reliability of the programming. The Copy feature is used to copy (or clone) all the settings from one DP6060 to other meters in about 20 seconds! The Copy function is a standard feature on all meters. It does not require a communications adaptor, only an optional cable assembly. The DP6060 minimizes the menu selections by auto-detecting the installed options to determine what menu navigation is required.

General Specifications

Display: Both displays are 6 digits (-99999 to 999999), red LEDs with leading zero blanking
Upper Display: 15 mm (0.60") high
Lower Display: 12 mm (0.46") high

Display Intensity: 8 intensity levels
Display Update Rate: 5/second (200 ms)
Overrange: Display flashes 999999
Underrange: Display flashes -99999
Display Assignment: The upper and lower displays may be assigned to process values for Channels A (Ch-A), B (Ch-B), or C (Ch-C), toggle between (Ch-A & Ch-B, Ch-A & Ch-C, Ch-B & Ch-C, and Ch-A, Ch-B, & Ch-C), toggle between Channel and units, show channel gross value (no tare) or toggle net (tare) and gross values, show relay set points, max and min values, or MODBUS input; the second display may also be set to show engineering units or be off, with no display
Front Panel: NEMA 4X (IP65)
Programming Methods: 4 front panel buttons, digital inputs, PC and software, MODBUS registers, or cloning using copy function
Noise Filter: Programmable from 2 to 199 (0 will disable filter)
Filter Bypass: Programmable from 0.1 to 99.9% of calibrated span
Recalibration: Calibrated at the factory. Recalibration is recommended at least every 12 months
Max/Min Display: Max (peak)/min (valley) readings reached by the process are stored until reset by the user or until power to the meter is cycled
Password: 3 programmable passwords restrict modification of programmed settings; Pass 1: Allows use of function keys and digital inputs; Pass 2: Allows use of function keys, digital inputs and editing set/reset points; Pass 3: Restricts all programming, function keys, and digital inputs

Non-Volatile Memory: All programmed settings are stored in non-volatile memory for a minimum of ten years if power is lost

Power Options: 85 to 265 Vac 50/60 Hz, 90 to 265 Vdc, 20 W maximum, or jumper selectable 12/24 Vdc $\pm 10\%$, 15 W maximum

Fuse (External, Required): UL recognized, 5 A maximum, slow blow; up to 6 meters may share one 5 A fuse

Isolated Transmitter Power Supply: 24 Vdc $\pm 5\%$ @ 200 mA maximum (standard), (12/24 Vdc powered models rated @ 100 mA maximum); 5 or 10 Vdc @ 50 mA maximum, selectable with internal jumper J4

Normal Mode Rejection: Greater than 60 dB at 50/60 Hz

Isolation: 4 kV input/output-to-power line; 500 V input-to-output or output-to-P+ supply

Overvoltage Category: Installation overvoltage category II; local level with smaller transient overvoltages than installation overvoltage category III

Operating Temperature Range: -40 to 65°C

Storage Temperature Range: -40 to 85°C

Relative Humidity: 0 to 90% non-condensing

Connections: Removable screw terminal blocks accept 12 to 22 AWG wire, RJ45 for external relays, digital I/O, and serial communication adapters

Enclosure: ½ DIN, high impact plastic, UL 94V-0, color: black

Mounting: ½ DIN panel cutout required: 92 x 45 mm (3.622 x 1.772"); two panel mounting bracket assemblies are provided

Tightening Torque: Screw terminal connectors: 5 lb-in (0.56 Nm)

Overall Dimensions: 119 W x 62 H x 143 mm D (4.68 x 2.45 x 5.64")

Weight: 269 g (9.5 oz)

Dual Process Input

Inputs: 2 inputs, each separately, field selectable: 0 to 20, 4 to 20 mA, 10V (0 to 5, 1 to 5, 0 to 10V), MODBUS PV (slave)

Channels: Channel A, Channel B, Channel C (math channel)

Accuracy: $\pm 0.03\%$ of calibrated span ± 1 count, square root and programmable exponent accuracy range: 10 to 100% of calibrated span

Temperature Drift: 0.005% of calibrated span/°C max from 0 to 65°C ambient, 0.01% of calibrated span/°C maximum from -40 to 0°C ambient

Signal Input Conditioning: Linear, square root, programmable exponent, or round horizontal tank volume calculation

Multi-Point Linearization: 2 to 32 points for PV or PV1; 2 to 8 points for PV2 (dual-scale level feature)

Programmable Exponent: 1.0001 to 2.9999

Low-Flow Cutoff: 0 to 999999 (0 disables cutoff function)

Decimal Point: Up to 5 decimal places or none: d.ddddd, dd.dddd, ddd.ddd, dddd.dd, ddddd.d, or ddddd

Calibration Range:

4 to 20 mA: Minimum span; input 1 and input 2: 0.15 mA

± 10 V: Minimum span; input 1 and 2: 0.10V

An Error message will appear if input 1 and input 2 signals are too close together

Input Impedance:

Voltage Ranges: Greater than 500 k Ω

Current Ranges: 50 to 100 Ω (depending on resettable fuse impedance)

Input Overload: Current input protected by resettable fuse, 30 Vdc max; fuse resets automatically after fault is removed

Relays

Rating: 2 or 4 SPDT (Form C) internal and/or 4 SPST (Form A) external; rated 3 A @ 30 Vdc and 125/250 Vac resistive load; 1/14 HP (≈ 50 W) @ 125/250 Vac for inductive loads such as contactors, solenoids, etc.

Noise Suppression: Recommended for each relay contact switching inductive loads

Deadband: 0 to 100% of span, user programmable

High or Low Alarm: User may program any alarm for high or low trip point; unused alarm LEDs and relays may be disabled (turned off)

Relay Operation: Automatic (non-latching), latching (requires manual acknowledge), sampling (based on time), pump alternation control (2 to 8 relays), off (disable unused relays and enable interlock feature, manual on/off control mode)

Time Delay: 0 to 999.9 seconds, on and off relay time delays; programmable and independent for each relay

Fail-Safe Operation: Programmable and independent for each relay

Note: Relay coil is energized in non-alarm condition. In case of power failure, relay will go to alarm state.

Auto Initialization: When power is applied to the meter, relays will reflect the state of the input to the meter

Serial Communications

Protocol: MODBUS RTU

Meter Address/Slave ID: 1 - 247

Baud Rate: 300 to 19,200 bps

Transmit Time Delay: Programmable between 0 and 199 ms

Data: 8 bit (1 start bit, 1 or 2 stop bits)

Parity: Even, odd, or none with 1 or 2 stop bits

Byte-to-Byte Timeout: 0.01 to 2.54 seconds

Turn Around Delay: Less than 2 ms (fixed)

Isolated 4 to 20 mA Transmitter Output

Output Source: Process variable (PV), max, min, set points 1 through 8, manual control setting, or MODBUS input

Scaling Range: 1.000 to 23.000 mA for any display range

Factory Calibration: 4.000 to 20.000 = 4 to 20 mA output

Analogue Output Programming: 23.000 mA maximum for all parameters: overrange, underrange, max, min, and break

Accuracy: $\pm 0.1\%$ of span ± 0.004 mA

Temperature Drift: 0.4 $\mu\text{A}/^\circ\text{C}$ maximum from 0 to 65°C ambient, 0.8 $\mu\text{A}/^\circ\text{C}$ maximum from -40 to 0°C ambient

Note: Analog output drift is separate from input drift.

Isolated Transmitter Power Supply:

Terminals I+ & R: 24 Vdc $\pm 5\%$ @ 40 mA maximum, may be used to power the 4 to 20 mA output or other devices

External Loop Power Supply: 35 Vdc maximum

Output Loop Resistance:

24 Vdc Power Supply: 10 Ω minimum, 700 Ω maximum

35 Vdc (External) Power Supply: 100 Ω minimum, 1200 Ω maximum

Digital I/O Expansion Module

Channels: 4 digital inputs and 4 digital outputs per module

System: Up to 2 modules for a total of 8 inputs and 8 outputs

Digital Input Logic:

High: 3 to 5 Vdc

Low: 0 to 1.25 Vdc

Digital Output Logic:

High: 3.1 to 3.3 Vdc

Low: 0 to 0.4 Vdc

Source Current: 10 mA maximum

Sink Current: 1.5 mA minimum

+5 V Terminal: To be used as pull-up for digital inputs only

4-Relay Expansion Module

Relays: 4 Form A (SPST) rated 3 A @ 30 Vdc and 125/250 Vac resistive load; 1/14 HP (≈ 50 W) @ 125/250 Vac for inductive loads

Meter Copy

The Copy feature is used to copy (or clone) all the settings from one DP6060 to other DP6060 meters in about 20 seconds! The Copy function is a standard feature on all meters. It does not require a communications adapter, only an optional cable assembly, model number DPA1200. See the ordering information for complete details



NEMA 4X Field Enclosures

Thermoplastic NEMA 4X enclosures are constructed for either indoor or outdoor use.



DP6060 with DPA2812 NEMA 4X field enclosure, shown smaller than actual size.

To Order Visit omega.com/dp6060 for Pricing and Details

Model No.	Description
Standard 85 to 265 Vac Models	
DP6060-6R0	Dual input process panel meter
DP6060-6R2	Dual input process panel meter with 2 relays
DP6060-6R3	Dual input process panel meter with 4 to 20 mA output
DP6060-6R4	Dual input process panel meter with 4 relays
DP6060-6R5	Dual input process panel meter with 2 relays and 4 to 20 mA output
DP6060-6R7	Dual input process panel meter with 2 relays and 4 to 20 mA output
Standard 12/24 Vdc Low Voltage Models	
DP6060-7R0	Dual input process panel meter
DP6060-7R2	Dual input process panel meter with 2 relays
DP6060-7R3	Dual input process panel meter with 4 to 20 mA
Sunlight Readable Models, 85 to 265 Vac	
DP6060-6H0	Dual input process panel meter
DP6060-6H2	Dual input process panel meter with 2 relays
DP6060-6H3	Dual input process panel meter with 4 to 20 mA output
Sunlight Readable Models, 12/24 Vdc Low Voltage	
DP6060-7H0	Dual input process panel meter
DP6060-7H2	Dual input process panel meter with 2 relays
DP6060-7H3	Dual input process panel meter with 4 to 20 mA output

Accessories

Model No.	Description
DPA1004	4-relay expansion module - field installable
DPA1044	4 digital inputs and 4 digital outputs module - field installable
DPA1232	RS232 serial adaptor - field installable
DPA1485	RS485 serial adaptor - field installable
DPA8008	USB serial adaptor - field installable
DPA7485-I	RS232 to RS422/485 isolated converter - field installable
DPA7485-N	RS232 to RS422/485 non-isolated converter - field installable
DPA8232-N	USB to RS232 non-isolated converter - field installable
DPA8485-I	USB to RS422/485 isolated converter - field installable
DPA8485-N	USB to RS422/485 isolated converter - field installable
DPA1002	DIN rail mounting kit for 2 expansion modules
DPA1200	Meter copy cable
DPA2811	Plastic NEMA 4X enclosure for one DP6070 temperature meter
DPA2812	Plastic NEMA 4X enclosure for two DP6070 temperature meters

Comes complete with 2 side mounting brackets and operator's manual. Free **CN6000-SOFT** software download available at omega.com/dp6060
Ordering Example: DP6060-6R2, temperature panel meter with 2 relays, and DPA8008, USB serial adaptor. **OCW-2**, OMEGACARESM extends standard 3-year warranty to a total of 5 years.